

BT8331 UNIVERSAL POP-IN, POP-OUT MENU BOARD MOUNTING SYSTEM

DEA



NAVATION AWARDS

TECHNOLOGY FINALIST

The BT8331 is a modular wall mounting system for menu board installations of any size and features pop-in, pop-out interface arms designed to aid installation and allow access to the rear of the screens for servicing and maintenance. As part of the System X range, the BT8331 features a contemporary, lightweight yet incredibly strong design with a high-end aesthetic quality and 8-point micro-adjustment for seamless screen alignment.

SPECIFICATION	
Recommended screen size	32" - 65"
Max load	50kg (per screen)
Depth (with micro-adjustment)	119mm to 133mm
Depth (popped out with micro-adju	stment) 298mm to 313mm
VESA® & non-VESA fixings	(max vertical dimension) 400mm*
Colour (VESA arms)	Black
Colour (horizontal rail)	Silver

*The VESA specification of the BT8331 refers to the **vertical dimension only**. All System X interface arms can be positioned as far along the rail as necessary. It is also possible to **increase the maximum vertical fixing to 600mm** by using **BT7564** interface adaptor arms (available separately). Please note that using these adaptors will increase the total depth on the install by 20mm.

FEATURES

- Universal design suitable for all sized screens up to 50kg (per screen)
- Features pop-in, pop-out function to allow access to the rear of screens
- for servicing and maintenance and to aid installation
- Tool-less micro-adjustments at 8 points for seamless display alignment
 Suitable for landscape or portrait mounting
- High-end aesthetic quality
- Safety screws help prevent unauthorised removal of screens
- Ideal for recess mounting menu boards
- Arms include locking screw to prevent accidental pop-out of screens
- Cable management included for a neat and tidy installation
- Multiple rail lengths available (rails can also be joined to create larger installs)



Tool-less micro-adjustment at 8 points for seamless display alignment



Push to open / push to close system provides quick and easy service access



of rows and orientation.

VESA

400

Multiple rail lengths available (rails can also be joined to create larger installs)



RAILS

CREATE YOUR MOUNTING SYSTEM ONLINE

SYSTEM X CONFIGURATION TOOL WILL CREATE A MOUNTING KIT TO SUIT YOUR NEED

SPECIFY YOUR VIDEO WALL & MENU BOARD REQUIREMENTS ONLINE AND OUR

There are thousands of System X configurations available! Visit our

online configuration tool to specify setups, number of screens, number

Try now at www.btechavmounts.com/systemx-configurator

OTHER COMPONENTS ...

....

Safety screws help prevent unauthorised removal of screens



TECHNICAL DRAWINGS

CREATING YOUR BT8331 KIT

BT8331 configurations are made to your exact requirements and, as a result, utilise a varying combination of System X components in order to create the perfect solution. Below are technical drawings for the standard components used in every BT8331 configuration: BT8390-VESA400MAP Pop-Out Interface Arms, BT8390-WFK2 Wall Fixing Kit and BT8390 Mounting Rails (available in the lengths shown). Please visit our System X online configuration tool at www.btechavmounts.com/systemx-configurator to specify your requirements. All dimensions will be automatically calculated and a complete mounting solution with all required parts will be created for you.



A

