



LTE700 IR Pass Distn Amp 8 Way

Art. Number 334094



LTE 700 8 Way IR Pass Amplifier

- LTE700 protected IR Pass Distribution Amplifier
- Distributes to multiple TV's around the home
- Allows control of Sky Digital receivers when used with TRIAX Digital Links and MOD103T Modulator
- 2 Input 8 Output
- · Short circuit protected in each output
- Power on LED
- Screened housing
- F-Connectors
- · Easy to mount fixing

Technical Specifications		
ORDER INFORMATION		
EAN Number	5702663340947	
CHARACTERISTICS		
Max. Output level dBμV	96.0 dBµV	
FREQUENCY RANGE		
Frequency Range DAB MHz	217230 MHz	
Frequency Range FM MHz	87.5108 MHz	
Frequency range UHF MHz	470694 MHz	
Frequency range VHF MHz	85230 MHz	
Output frequency range MHz	85694 MHz	
GAIN		
Gain dB	10 +/-2 dB	
Noise figure dB	<5 dB	
ELECTRICAL		
Impedance Ω	75 Ω	



connecting the future

Technical Specifications

OPERATIONAL	
AC Supply voltage VAC	230 ±10% / 50Hz VAC
CONNECTORS	
Number of inputs	2
Number of outputs	8
MECHANICAL	
Colour	RAL 7016 - Anthracite grey
Packaging Depth m	0.130 m
Packaging Height m	0.060 m
Total Weight kg	0.660 kg
Packaging Width m	0.250 m
Net Weight kg	0.550 kg
Packing QTY	1
Remarks	fully screened within plastic housing
Tara Weight kg	0.110 kg
Packaging Volume m3	0.002 m3

29-09-2022 2/2 triax.com